

www.ListenTech.com

Specify Part Number

LA-261



Lavalier Microphone

- Use with Listen's LT-700 Portable Transmitter
- For vocal/speech applications
- Non-directional microphone picking up audio in all directions
- Outstanding audio performance
- Ideal for use when unobtrusive placement and high performance are critical
- Clips onto a shirt, collar or garment near the neck
- The transmitter antenna is built into the microphone cord

| Specifications | |
|--------------------|----------------------|
| Frequency Response | 20 Hz - 15 KHz |
| Impedance | Less than 2.2 K ohms |
| Connector | 3.5 mm mono |
| Phantom Power | 3 VDC required |
| Cable Length | 36 in. (92 cm) |
| Weight | 4 oz. (113 g) |
| Color | Black |

Specify Part Number

LA-262



Over-the-Head Microphone

- Use with Listen's LT-700 Portable Transmitter
- For vocal/speech applications
- Superior aural performance
- Adjustable microphone boom
- The transmitter antenna is built into the microphone cord

| Sp | ec | ifi | ca | tic | ns | 5 |
|----|----|-----|----|-----|----|---|
| _ | | | | _ | | |

| Frequency Response | 30 Hz - 5 KHz |
|--------------------|----------------|
| Impedance | 680 ohms |
| Connector | 3.5 mm mono |
| Phantom Power | 3 VDC required |
| Cable Length | 36 in. (92 cm) |
| Weight | 8 oz. (227 g) |
| Color | Black |


Listen Technologies Corporation

8535 South 700 West, Suite A

Sandy, UT 84070-2515 U.S.A.

Phone: 1.801.233.8992 or 1.800.330.0891

Fax: 1.801.233.8995 Email: info@ListenTech.com







Specify Part Number

LA-264



Over-the-Head Microphone Replacement Cushions

- Contains 1 windscreen and 2 ear cushions
- Fits LA-262 and LA-272

Specify Part Number

LA-270



Noise Canceling Microphone

- Use with Listen's LT-700 Portable Transmitter
- Great for high noise environments
- Picks up voice and transmits to receivers
- Designed to cancel ambient noise
- Fits around the back of your head under hair
- Directional microphone picks up audio directly in front of the mic only
- Fully adjustable
- The transmitter antenna is built into the microphone cord

| Specifications | |
|--------------------|-----------------|
| Frequency Response | 300 Hz - 10 KHz |
| Impedance | 1 K ohms |
| Connector | 3.5 mm mono |
| Phantom Power | 3 VDC required |
| Cable Length | 55 in. (1.4 m) |
| Weight | 2 oz. (59 g) |
| Color | Black |



Specify Part Number

LA-272



- Noise Canceling Microphone

 Use with Listen's LT-700 Portable Transmitter and Listen portable receiver or other audio input
- Two 3.5 mm connectors one for microphone and one for earphone
- For vocal/speech applications
- Active earpiece
- Superior aural performance
- Adjustable microphone boom
- The transmitter and receiver antenna is built into the microphone/earphone cord

| Microphone Specifications | | Earphone Specifica | Earphone Specifications | | |
|---------------------------|----------------|--------------------|-------------------------|--|--|
| Frequency Response | 30 Hz - 5 KHz | Frequency Response | 20 Hz - 20 KHz | | |
| Impedance | 680 ohms | Impedance | 32 ohms | | |
| Connector | 3.5 mm mono | Maximum Input | 130 mW | | |
| Phantom Power | 3 VDC required | Connector | 3.5 mm mono | | |
| Cable Length | 36 in. (92 cm) | Cable Length | 36 in. (92 cm) | | |
| Weight | 8 oz. (227 g) | | | | |
| Color | Black | | | | |

Specify Part Number

LA-274



Hand Held Microphone

- Use with Listen's LT-700 Portable Transmitter
- For vocal/speech applications
- Directional microphone (cardoid pattern) helps to eliminate ambient noise
- Outstanding audio performance
- Table top adapter allows for a table or podium use
- Mute switch on microphone
- The transmitter antenna is built into the microphone cord

| Specifications | |
|--------------------|----------------|
| Frequency Response | 20 Hz - 15 KHz |
| Impedance | 2.2 K ohms |
| Connector | 3.5 mm mono |
| Phantom Power | 3 VDC required |
| Cable Length | 36 in. (92 cm) |
| Weight | 4 oz. (113 g) |
| Color | Black |



Specify Part Number

LA-276



Collar Microphone

- Use with Listen's LT-700 Portable Transmitter
- For vocal/speech applications
- Directional microphone (cardoid pattern) rejects sound from rear and sides of mic
- Fits around the back of your neck and around your collar
- Fully adjustable, comfortable to wear for long periods
- Good microphone for placement directly in front of mouth
- The transmitter antenna is built into the microphone cord

| Specifications | |
|--------------------|-------------------|
| Frequency Response | 300 HZ - 18 KHz |
| Impedance | 1 K ohms |
| Connector | 3.5 mm mono |
| Phantom Power | 1.5 VDC required |
| Mic Length | 22 in. (55.9 cm) |
| Cable Length | 48 in. (121.9 cm) |
| Weight | 4 oz. (113 g) |
| Color | Black |

Specify Part Number

LA-277



Conference Microphone

- Use with Listen's LT-700 Portable Transmitter
- For vocal/speech applications in a conference room or group discussion
- Omni-directional microphone receives audio from entire surrounding area
- Outstanding audio performance
- Low profile design
- Highly durable case construction
- The transmitter antenna is built into the microphone cord

| Specifications | |
|--------------------|---|
| Frequency Response | 20 HZ - 12 KHz |
| Impedance | 1 K ohms |
| Connector | 3.5 mm mono |
| Phantom Power | 3 VDC required |
| Cable Length | 10 ft. (77 cm) |
| Dimensions | 2.3 in. (58 mm) tall by 1.4 in. (35 mm) in diameter |
| Weight | 4 oz. (113 g) |
| Color | Black |



Specify Part Number

LA-278



Behind-the-Head Microphone

- Use with Listen's LT-700 Portable Transmitter
- Non-directional microphone picking up audio in all directions
- Outstanding audio performance
- Ideal for use when unobtrusive placement and high performance are critical
- Designed to cancel ambient noise
- The transmitter antenna is built into the microphone cord
- Fits securely over ears and around the back of the neck, under hair
- Great for high noise environments

| Specifications | pec | ific | atic | ons |
|----------------|-----|------|------|-----|
|----------------|-----|------|------|-----|

Frequency Response 300 Hz - 10 KHz

Impedance 1 K ohms

Connectors 3.5 mm mono

Phantom Power 3 VDC Color black

Cable Length 55 in. (1.4 m) Weight 2 oz. (59 g)

Specify Part Number

LA-263



LT-700 Line/Microphone Y Cable

Provides a Y-connection for a microphone and a line level audio source such as a CD or MP3 player.